

S-1000-SFP Gigabit Media Converters

1000Base-T to 1000Base-X Fiber Mode Conversion



- 1000Base-T to 1000Base-X Fiber SFP Media Converters
- Advanced features - Smart Link Pass-Through, Fiber Fault Alert, Auto-MDIX and Loopback
- Empty slot for **Cisco** and other **industry standard Gigabit Fiber SFPs**

Perle's line of feature rich **Gigabit SFP Media Converters** transparently connect Gigabit copper to SFP for multimode or single mode fiber. Our Gigabit Ethernet to Fiber Converters provide an economical path to extend the distance of an existing network, the life of non-fiber based equipment, or the distance between two devices. The pluggable fiber optics port allows for flexible network configurations using **SFP transceivers supplied by Perle, Cisco** or other manufacturers of MSA compliant SFPs.

Network Administrators can "see-everything" with Perle's advanced features such as Auto-Negotiation, Auto-MDIX, Link Pass-Through, Fiber Fault Alert, and Loopback. This allows for more efficient troubleshooting and less on-site maintenance. These cost and time saving features, along with a lifetime warranty and free worldwide technical support, make Perle's **Gigabit SFP Converters** the smart choice for IT professionals.

Gigabit SFP Media Converter Features

Auto-Negotiation (802.3ab)

The media converter supports auto negotiation. The 1000Base-X fiber interface negotiates according to 802.3 clause 37. The 1000Base-T negotiates according to 802.3 clause 28 and 40. The 1000Base-X will link up with its partner after the highest common denominator (HCD) is reached and the copper has linked up with its partner. The 1000Base-X will continue to cycle through negotiation transmitting a remote fault of offline (provided this is enabled through the switch setting) until the copper is linked up and the HCDs match.

The media converter supports auto-negotiation of full duplex, half duplex, remote fault, full duplex pause, asymmetric pause and Auto MDI-X.

Auto-MDIX with Skew Correction

Auto-MDIX (automatic medium-dependant interface crossover) detects the signaling on the 1000Base-T interface to determine the type of cable connected (straight-through or crossover) and automatically configures the connection when enabled. The media converter can also correct for wires swapped within a pair.

The media converter will adjust for up to 64ns of delay skew between the 1000Base-T pairs.

Smart Link Pass-Through

When the Link Mode switch is placed into Smart Link Pass-Through mode, the 1000Base-T port will reflect the state of the 1000Base-X media converter port. This feature can be used whether fiber auto-negotiation is enabled or disabled.

Fiber Fault Alert

With Fiber Fault Alert the state of the 1000Base-X receiver is passed to the 1000Base-X transmitter. This provides fault notification to the partner device attached to the 1000Base-X interface of the media converter. If the 1000Base-X transmitter is off as a result of this fault it will be turned on periodically to allow the condition to clear should the partner device on the 1000Base-X be using a similar technique. This eliminates the possibility of lockouts that occur with some media converters. Applies only when fiber auto-negotiation is disabled.

Pause (IEEE 802.3x)

Pause signaling is an IEEE feature that temporarily suspends data transmission between two devices in the event that one of the devices becomes overwhelmed. The media converter supports pause negotiation on the 1000Base-T fiber connection and 1000Base-X fiber connection.

Duplex

Full and half duplex operation supported.

Jumbo Packets

Transparent to jumbo packets up to 10KB.

VLAN

Transparent to VLAN tagged packets.

Remote Loopback

Capable of performing a loopback on the 1000Base-X fiber interface.

Specifications

Lifetime limited warranty	Reach, RoHS and WEEE Compliant	HTSUS Number: 8517.62.0020	UNSPSC Code: 43201553	ECCN: 5A991
----------------------------------	---------------------------------------	--------------------------------------	---------------------------------	-----------------------



Power

Input Supply Voltage	6 - 30 vDC, unregulated (12 vDC Nominal)
Current	250 mA
Power Consumption	3.0 watts
Power Connector	5.5mm x 9.5mm x 2.1mm barrel socket

Power Adapter

Universal AC/DC Adapter	100-240v AC, regulated DC adapter included
-------------------------	--

Indicators

Power / TST	This green LED is turned on when power is applied to the media converter. Otherwise it is off. The LED will blink when in Loopback test mode.
Fiber link on / Receive activity (LKF)	This green LED is operational only when power is applied. The LED is on when the 1000Base-X link is on and flashes with a 50% duty cycle when data is received. The LED will slow blink when the 1000Base-X interface has been taken down as a result of a fault on the 1000Base-T interface.

Copper link on / Receive activity (LKC)	This green LED is operational only when power is applied. The LED is on when the 1000Base-T link is on and flashes with a 50% duty cycle when data is received. The LED will slow blink when the 1000Base-T interface has been taken down as a result of a fault on the 1000Base-T interface.
Switches - accessible through a side opening in the chassis	
Auto-Negotiation	<ul style="list-style-type: none"> • <i>Enabled (Default - Up)</i> - In this mode the 1000Base-X and the 1000Base-T will negotiate to the HCD of the two link partners. The 1000Base-X will link up after the negotiation is completed and the 1000Base-T has linked up. • <i>Disabled</i> - The 1000Base-X will not use auto negotiation. The 1000Base-T will negotiate to the HCD of the Switch settings and the link partner.
Link Mode	<p>Link Mode provides a transparency to the state of the copper link allowing for simplified trouble shooting from the devices connected to the media converter.</p> <p><i>Normal (Default — Up)</i></p> <ul style="list-style-type: none"> • With Fiber Auto Negotiation enabled when the 1000Base-T link goes down the 1000Base-X link is brought down. The 1000Base-X link will advertise Remote Fault (Link Fault). • With Fiber Auto Negotiation disabled the state of the 1000Base-T link has no effect on the 1000Base-X link. <p><i>Smart Link Pass Through (Down)</i></p> <ul style="list-style-type: none"> • With Fiber Auto Negotiation enabled the behavior is as follows. When the 1000Base-T link goes down the 1000Base-X link is brought down. The 1000Base-X link will advertise Remote Fault (Link Fault). When Remote Fault (Link Fault) is received on the 1000Base-X interface the 1000Base-T transmitter will be turned off. When the 1000Base-T receiver is off the 1000Base-X transmitter will be turned off. When the 1000Base-X receiver goes off the 1000Base-T transmitter will be turned off. • With Fiber Auto-Negotiation disabled the behavior is as follows. When the 1000Base-T receiver is off the 1000Base-X transmitter will be turned off. When the 1000Base-X receiver goes off the 1000Base-T transmitter will be turned off.

Pause	<p>When Fiber Auto Negotiation is disabled Pause should only be enabled when all devices connected to the media converter support pause.</p> <ul style="list-style-type: none"> • <i>Enabled (Default)</i> - The Media converter will advertise Pause capable, Asymmetric pause not needed during Auto-Negotiation. • <i>Disabled</i> - The Media converter will advertise that it does not have Pause capability during Auto-Negotiation.
Fiber Fault Alert	<p>The Fiber Fault Alert switch has meaning when Auto-Negotiation is disabled</p> <ul style="list-style-type: none"> • <i>Enabled (Default - Up)</i> - When the 1000Base-X receiver is off the 1000Base-X transmitter is turned off. Periodically the 1000Base-X receiver will be turned on for a short period to allow the condition to clear if the 1000Base-X link partner is using a similar feature. • <i>Disabled (Down)</i>
Duplex	<ul style="list-style-type: none"> • <i>Full (Default-Up)</i> - The media converter will advertise Full Duplex Capable, Half Duplex Capable. • <i>AUTO (Down)</i> - The Media converter will advertise Full Duplex Not Capable, Half Duplex Capable.
Remote Loopback	<p>The media converter can perform a loopback on the 1000Base-X fiber interface.</p> <ul style="list-style-type: none"> • <i>Disabled (Default - Up)</i> • <i>Enabled</i> - The 1000Base-X receiver is looped to the 1000Base-X transmitter. The 1000Base-T transmitter is taken off the interface.
Connectors	
1000Base-T	RJ45 connector, 4 pair CAT5 UTP cable or better
Magnetic Isolation	1.5kv
Small Form Factor Pluggable (SFP) slot	<ul style="list-style-type: none"> • Empty slot for 100Base-X SFP modules supplied by Perle, Cisco or other manufacturers of MSA compliant SFPs. • Hot insertion and removable (hot swappable).
Packet Transmission Characteristics	
Bit Error Rate (BER)	<10 ⁻¹²

Environmental Specifications	
Operating Temperature	0°C to 50°C (32°F to 122°F)
Storage Temperature	minimum range of -25°C to 70°C (-13°F to 158°F)
Operating Humidity	5% to 90% non-condensing
Storage Humidity	5% to 95% non-condensing
Operating Altitude	Up to 3,048 meters (10,000 feet)
Heat Output (BTU/HR)	10.2
MTBF (Hours)*	<ul style="list-style-type: none"> • Without power adaptor: 745,000 Hours • With power adaptor: 375,000 Hours <i>Calculation model based on MIL-HDBK-217-FN2 @ 30°C</i>
Chassis	Metal with an IP20 ingress protection rating
Mounting	
Din Rail Kit	Optional
Wall / Rack Mount Kit	Optional
Product Weight and Dimensions	
Weight	0.3 kg, 0.66 lbs
Dimensions	120 x 80 x 26 mm, 4.7 x 3.1 x 1.0 inches
Packaging	
Shipping Weight	0.58 kg, 1.3 lbs
Shipping Dimensions	170 x 280 x 70 mm, 6.7 x 10.2 x 2.8 inches

Regulatory Approvals	
Emissions	<ul style="list-style-type: none"> FCC Part 15 Class A, EN55022 Class A CISPR 22 Class A CISPR 32:2015/EN 55032:2015 (Class A) CISPR 35/EN 55035 EN61000-3-2
Immunity	EN55024
Electrical Safety	<ul style="list-style-type: none"> UL/EN/IEC 62368-1 CAN/CSA C22.2 No. 62368-1 UL 60950-1 IEC 60950-1(ed 2); am1, am2 EN 60950-1:2006+A11:2009+A1:2010+A12:2011+A2:2013 CE

Product List



S-1000-SFP - Gigabit Ethernet Stand-Alone Media Converter. 1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-X - SFP slot (empty)

Power Cord & Part Number(s)

USA	UK	EU	SA	AUS	None
05050184	05050181	05050182	05050185	05050186	05050188

Related Accessories

Accessories



DIN Rail Mounting Kit for 4 & 8 port IOLAN desktop models, all Stand-Alone Media Converters and all Stand-alone Ethernet Extenders. Two of these brackets are required for the 8 port STS8-D model.

04030840



Standalone media converter wall / rack mount bracket

05059999

Power Supplies



UK 12VDC / 12W power adapter with Barrel connector for Perle Device Servers, Media Converters, and Ethernet

04031581



EU 12VDC / 12W power adapter with Barrel connector for Perle Device Servers, Media Converters, and Ethernet

04031582



USA 12VDC / 12W power adapter with Barrel connector for Perle Device Servers, Media Converters, and Ethernet

04031584



Australia 12VDC / 12W power adapter with Barrel connector for Perle Device Servers, Media Converters, and Ethernet

04031586