

S-4GPT-DSFP Fiber Mode Converter

SFP to SFP Protocol Transparent Media Converter



- Easy Fiber to Fiber network extension to remote locations
- Provide wavelength conversion for CWDM and DWDM transponder applications
- Protocol-transparency support for all network protocols
- Support for SFP transceivers with data rates up to 4.25 Gbps
- Reliable operation with advanced features like **Smart Link Pass-Through** and Fiber Fault Alert

Perle's feature rich **SFP to SFP protocol and rate-transparent media converters** enable network administrators to incorporate multiple fiber types and wavelengths in, or between, networks through **fiber to fiber mode conversion**. Using this technology will result in significant cost savings when compared to replacing an optical blade on network equipment. Easily extend a network to remote locations by converting:

- Multimode to Multimode
- Multimode to Single Mode
- Single Mode to Single Mode
- Dual to single fiber (Duplex to Simplex BiDi)

SFP to SFP Conversion

The **S-4GPT-DSFP Fiber Mode Converter** comes with two empty SFP slots. This allows for flexible network configurations using **SFP fiber transceivers supplied by Perle, Cisco** or other manufacturers of MSA compliant SFPs. Adapting to different fiber types, distances and wavelengths is made simple by **mixing and matching SFP's as needed** for maximum flexibility across a variety of topologies and network architectures. The hot-swappable nature of SFPs allow for easy configuration and future upgrades as network demands evolve by simply upgrading a single SFP instead of replacing the entire fiber mode converter.

Convert different wavelengths (WDM Transponders)

SFP transceivers also enable the **S-4GPT-DSFP Fiber Mode Converter** to operate as a **Wave Division Multiplexing (WDM) transponder**. Also referred to as Bi-Directional (BiDi) or Simplex, WDM Transponders help network administrators take advantage of the cost savings in both material and labour associated with Single Strand Fiber. WDM uses separate transmit and receive frequencies to **communicate on a single fiber strand**. WDM technology relies on the fact that optical fibers can carry many wavelengths of light simultaneously without interaction between each wavelength. Thus, a single fiber can carry many separate wavelength signals or channels simultaneously. WDM systems are divided into different wavelength patterns, conventional/coarse (**CWDM**) and dense (**DWDM**).

S-4GPT-DSFP Fiber Mode Converter Features

Network Administrators can “see-everything” Perle’s advanced features such as Smart Link Pass-Through and Fiber Fault Alert. This allows for more efficient troubleshooting and less on-site maintenance. These cost and time saving features, along with a **lifetime warranty and free worldwide technical support**, make the **S-4GPT-DSFP Fiber Mode Converter** the smart choice for IT professionals.

Protocol Transparency

Transparent to all protocols (including but not limited to)

- Ethernet : 10Base-FL
- Fast Ethernet : 100Base-X
- Gigabit Ethernet (1.25G , 2.5G) : 1000Base-X
- GR-253-CORE : ATM/SONET (OC-3, OC-12, OC-48)
- G.957 : SDH (STM-1, STM-4, STM-16)
- Fibre Channel: (FC-1, FC-2, FC-4)
- FDDI, IBM protocols ESCON and FICON
- Video protocols (DVB, SDI, HD-SDI, SMTPE)

Rate Transparency

Supports SFP data rates up to 4.25Gbps.

Smart Link Pass-Through



- Smart Link Pass-Through when enabled ensures that the link state on a fiber connection is directly reflected through the media converter to the other connection. If link is lost on one of the connections, then the other link will be brought down by the media converter. This feature applies when both SFP slots are occupied.
- If set in Standard Mode, the link is kept active. The unit will transmit a 25Mhz keep-alive signal to artificially keep the link up.

Fiber Fault Alert

If the media converter module detects a loss of fiber, it will immediately notify the fiber link partner that an error condition exists.

Power Strain Relief strap

A strain relief strap is provided to ensure a solid and secure power connection to the media converter. Ideal for areas that may be exposed to any vibration.


Specifications				
Lifetime limited warranty	Reach, RoHS and WEEE Compliant	HTSUS Number: 8517.62.0020	UNSPSC Code: 43201553	ECCN: 5A991
				
Power				
Input Supply Voltage	6 - 30 vDC, unregulated (12 vDC Nominal)			
Current	325mA @ 12VDC			
Power Consumption	4 watts			
Power Connector	5.5mm x 9.5mm x 2.1mm barrel socket			
Power Adapter				
Universal AC/DC Adapter	100-240v AC, regulated DC adapter included			
Indicators				
Power	This green LED is turned on when power is applied to the media converter. This LED is off when there is no power supplied. A Blinking LED will indicate that a hardware error has been detected.			
LK1	LED is ON when a signal is detected on LK1. LED is OFF when there is no signal.			
LK2	LED is ON when a signal is detected on LK2. LED is OFF when there is no signal.			

Switches - accessible through a side opening in the chassis	
Link Mode	<p>Smart Link Pass-Through when enabled (Default) ensures that the link state on a fiber connection is directly reflected through the media converter to the other connection. If link is lost on one of the connections, then the other link will be brought down by the media converter. This feature applies when both SFP slots are occupied.</p> <p>If set in Standard Mode, the link is kept active. The unit will transmit a 25Mhz keep-alive signal to artificially keep the link up.</p>
Fiber Fault Alert	<p>If the media converter module detects a loss of fiber, it will immediately notify the fiber link partner that an error condition exists.</p> <p><i>Disabled (Default).</i> The Media Converter will not monitor for fiber fault.</p>
Multi-speed SFP	<p>When enabled, identifies that the SFPs inserted are MSA complaint SFPs that have a multi-rate capability.</p> <p>When disable (Default), no action is performed in this context.</p>
Rate Select	<p>This enables rate selection when using dual-rate capable SFPs. If the “Multi-Speed SFP” select switch is in the “Disabled” position, this switch is ignored.</p> <ul style="list-style-type: none"> • High Speed - UP (default) • Low Speed – DOWN
2 x SFP Slots	
SFPs	<p>SFP line rates up to 4.25Gbps are supported. The SFPs occupying each slot in the media converter must be operating at the same speed.</p> <p>SFP power level 1 and 2 are supported.</p>
Environmental Specifications	
Operating Temperature	0°C to 50°C (32°F to 122°F)
Storage Temperature	minimum range of -25°C to 70°C (-13°F to 158°F)
Operating Humidity	5% to 90% non-condensing
Storage Humidity	5% to 95% non-condensing

Operating Altitude	Up to 3,048 meters (10,000 feet)
Heat Output (BTU/HR)	13.65
MTBF	<ul style="list-style-type: none"> • 931,619 Hours w/o power adapter • 416,965 Hours w/ power adapter <i>MTBF Calculation model based on MIL-HDBK-217-FN2 @ 30°C</i>
Chassis	Metal with an IP20 ingress protection rating
Mounting	
Din Rail Kit	Optional
Wall/Rack Mount Kit	Optional
Product Weight and Dimensions	
Weight	0.3 Kg, 0.7 lbs
Dimensions (W x H x D)	120 x 80 x 26 mm, 4.7 x 3.1 x 1.0 inches
Packaging	
Shipping Weight	0.55 kg, 1.2 lbs
Shipping Dimensions	170 x 260 x 70 mm, 6.7 x 10.2 x 2.8 inches
Regulatory Approvals	
Emissions	<ul style="list-style-type: none"> • FCC Part 15 Class A, EN55022 Class A • CISPR 22 Class A • CISPR 32:2015/EN 55032:2015 (Class A) • CISPR 35/EN 55035 • EN61000-3-2
Immunity	EN55024

Electrical Safety	<ul style="list-style-type: none"> • UL/EN/IEC 62368-1 • CAN/CSA C22.2 No. 62368-1 • UL 60950-1 • IEC 60950-1(ed 2); am1, am2 • EN 60950-1:2006+A11:2009+A1:2010+A12:2011+A2:2013 • CE
-------------------	--

Product List

 S-4GPT-DSFP - Protocol Transparent Stand-Alone Media Converter with dual SFP slots (empty). Supports two SFPs with identical speeds up to 4.25 Gbps. AC adapter included					
Power Cord & Part Number(s)					
USA	UK	EU	SA	AUS	None
05060574	05060571	05060572	05060575	05060576	05060578

Related Accessories

Accessories



DIN Rail Mounting Kit for 4 & 8 port IOLAN desktop models, all Stand-Alone Media Converters and all Stand-alone Ethernet Extenders. Two of these brackets are required for the 8 port STS8-D model.

04030840



Standalone media converter wall / rack mount bracket

05059999

Power Supplies



UK 12VDC / 12W power adapter with Barrel connector for Perle Device Servers, Media Converters, and Ethernet

04031581



EU 12VDC / 12W power adapter with Barrel connector for Perle Device Servers, Media Converters, and Ethernet

04031582



USA 12VDC / 12W power adapter with Barrel connector for Perle Device Servers, Media Converters, and Ethernet

04031584



Australia 12VDC / 12W power adapter with Barrel connector for Perle Device Servers, Media Converters, and Ethernet

04031586